



















































Re:connect Overview Interfaces								Version 1.26	
								11.06.2018	
Interface	Article-No.	Software status	Liste of TVs	Derivatives & other TVs	Note	Cabling	Connector Typ	Cabling RS 232	
Revox									
M200-1*	1.551.086.00	from V2.00	E642 MK-3		From serial number SN 6420002xxx			SubD9 to SubD25	ST-ST 2-3 / 3-2 / 5-7 Art. Nr. 1.510.100.40
M203-1	1.551.067.00	from V2.00							
			E642 MK-4	E642 MK-5 SN6420004xxx	From serial number SN 6420003xxx			2 x SubD9	ST-ST 2-3 / 3-2 / 5-5
			M710	M650				2 x SubD9	ST-ST 2-2 / 3-3 / 5-5
			42HD		from SN 01100			2 x SubD9	ST-BU 2-2 / 3-3 / 5-5
		from V2.09	CLUX CPRO 3D42S	HDMI Switcher				2 x SubD9	ST-ST 2-3 / 3-2 / 5-5
		from V2.10	Gefen GTB 6x2, 4x2	HDMI Switcher				2 x SubD9	ST-ST 2-3 / 3-2 / 5-5
Pioneer									
			PDP 5000 EX		Activate RS232 function within OSD			2 x SubD9	ST-BU 2-3 / 3-2 / 5-5
M200-2*	1.551.086.02	from V2.00	PDP 506 FDE		Deactivate SR+ Mode			2 x SubD9	ST-BU 2-3 / 3-2 / 5-5
M203-2	1.551.067.02	from V2.00	PDP 506 XDE-Cfromle		Deactivate SR+ Mode			2 x SubD9	ST-BU 2-3 / 3-2 / 5-5
			PDP 506 XDE-DVBT		Deactivate SR+ Mode			2 x SubD9	ST-BU 2-3 / 3-2 / 5-5
			PDP 507 XA	427 XA, 4270 XA	Deactivate SR+ Mode			2 x SubD9	ST-BU 2-3 / 3-2 / 5-5
		from V2.00	PDP 508 XD	5080 XD, 428 XD, 4280 XD	Set baud rate to 9600			2 x SubD9	ST-BU 2-3 / 3-2 / 5-5
		from V2.00	PDP 607 XD					2 x SubD9	ST-BU 2-3 / 3-2 / 5-5
			PDP 60 MXE20	50 MXE20				2 x SubD9	ST-BU 2-2 / 3-3 / 5-5
			PDP 615 EX					2 x SubD9	ST-BU 2-2 / 3-3 / 5-5
		from V2.01	LCD KRL-32V					2 x SubD9	ST-BU 2-2 / 3-3 / 5-5
		from V2.01	LCD KRL-37V					2 x SubD9	ST-BU 2-2 / 3-3 / 5-5
		from V2.01	LCD KRL-46V					2 x SubD9	ST-BU 2-2 / 3-3 / 5-5
		from V2.01	PDP LX-5090	LX-6090				2 x SubD9	ST-BU 2-3 / 3-2 / 5-5
		from V2.01	PDP LX-5090H	KRP-500A, KRP-600A, KRP-500M, KRP-600M, LX-6090H,				2 x SubD9	ST-BU 2-3 / 3-2 / 5-5
LOEWE									
M200-4*	1.551.086.03	from V2.00	≥ Chassis L2700	From Loewe chassis L2700 (or higher) with the following SW versionen: PCUART 3.1 or higher TV application software version: V2.2.x or higher				2 x SubD9	ST-ST 2-3 / 3-2 / 5-5
M203-4	1.551.067.03	from V2.00		Loewe TV-Liste 8 Spheros R32, R37/Compose 40, 46, 52/Selection 32, 40, 46 Xelos 32", 37", 42"/Connect 32", 37", 42" * retrofit RS232 interface, Loewe Accessories					
		from V2.04	Chassis SL 1xx	from Loewe Chassis SL 1xx V3.0.0 3D TVs from SL15x require Software from V5.20	Requires special RS232 cable			SubD9 to RJ12 6P6C	ST-ST 2-5 / 3-3 / 5-2
		from V2.09	Chassis SL 2xx	Loewe Chassis SL 2xx requires Software packet PV2.3.21 or higher	Requires special RS232 cable			SubD9 to RJ12 6P6C	ST-ST 2-5 / 3-3 / 5-2
		from V2.10	Chassis SL 3xx	from Loewe Chassis SL 3xx requires Software packet V3.0.41 or higher	Requires special RS232 cable			SubD9 to RJ12 6P6C	ST-ST 2-5 / 3-3 / 5-2
		from V2.18	Chassis SL4XX SSyst 0 - 2		Requires special RS232 cable			SubD9 to RJ12 6P6C	ST-ST 2-5 / 3-3 / 5-2

Sharp			All LCD TVs with RS232 interface, ausser 320 Serie.					2 x SubD9	ST-BU 2-2 / 3-3 / 5-5
M200-8*	1.551.086.07	from V2.00							
M203-8	1.551.067.07	from V2.00							

LG			All LCD TVs with RS232 interface.					2 x SubD9	ST-BU 2-2 / 3-3 / 5-5
M200-9*	1.551.086.08	from V2.06							
M203-9	1.551.067.08	from V2.06							
		from V2.07	Devices with 4 x multi tuner						
		from V2.08	HDMI Switch CLUX C81C						

Agath			All Agath TVs with RS232 interface from 2011					2 x SubD9	ST-ST 2-3 / 3-2 / 5-5
M200-A	1.551.086.09	from V2.06							
M203-A	1.551.067.09	from V2.06							
		from V2.09	Agath with DVB-C Tuner					2 x SubD9	ST-ST 2-3 / 3-2 / 5-5

Gefen HDMI All interfaces with the exception of M203 KNX		from V2.00	4 x 1 Switch					2 x SubD9	ST-ST 2-3 / 3-2 / 5-5
			4 x 2 Switch						
			6 x 2 Switch						

CLUX HDMI All interfaces with the exception of M203 KNX		from V2.06	4 x 1 Switch	Cypress CLUX -41AT				2 x SubD9	ST-ST 2-3 / 3-2 / 5-5
	M200-1 Revox from V 2.09		4 x 2 Switch	CYPRESS CPRO_3D42S					
	M203-1 Revox from V 2.09								
	M203-9 LG from V 2.08		8 x 1 Switch	Cypress CLUX - C81C					

Cinamateq Only M203-1		from V2.06	Scaler	picture optimizer plus II				2 x SubD9	ST-ST 2-3 / 3-2 / 5-5

* M200		from version V2.0		Requires a Processor 644P as well as a 20V DC feed by a power supply for a proper Relais operation. There is no Trigger IN and 0-10 Volts output available in the side rooms.					
--------	--	-------------------	--	---	--	--	--	--	--

Subject to errors and technical amendments. If third-party companies change or eliminate the RS232 protocols of their devices, Revox can no longer give any guarantee for a proper operation of the serial interfaces M200 resp. M203.