


STUDIOMASTER A200 Room Speaker

Active speaker with true-to-the-original studio sound quality. Integrated bass reflex technology. Simple operation on the product and via Revox App. The control panel and integrated display allow you to control and access music sources at any time, even without the Revox App. Battery and mains operation possible. With Multiuser 3.0 software.



Front view A200



Back view A200



Display view A200



TECHNICAL DATA

STUDIOMASTER A200

Order No.	black 142020100 white 142020200	Sources	Analog In (Ø 3,5mm) , Bluetooth, Air-Play 2, iRadio, Tidal, Deezer, Spotify
Price incl. VAT	€/CHF 495,-	Ports	1 x USB-C PD 45W, 1 x LAN, 1 x AUX-IN, 1 x Speaker Output for P100, 1 x USB (Service)
Colors	black, white	Battery operation	min. 12 hours mono/stereo
Dimensions H x W x D (mm)	222 x 100	Combination options	- A200 with A200 - wireless - A200 with P100 - wired - Integration into a Multiuser 3.0 setup
Weight (kg)	1,1		
Speaker	1 x Ø 70 mm Fullrange		
Frequency range	52Hz...20kHz (-3dB)		
Sound pressure	max. 95dB/ 1m		
Performance	1x 20W mono, 2x 20W stereo		
Power consumption	< 3W Standby < 4W Normal operation without signal		



REVOX
Multiuser

REVOX MULTIUSER

For more than 30 years, Revox has been a leading provider of special solutions for multi-room systems, bringing music of the highest audio quality simultaneously and appropriately into many living rooms. Music playback is uncompressed and loss-free, with minimal response time and absolutely synchronized in every room.

Revox Multiuser systems go even further than conventional multiroom systems.

The new Multiuser 3.0 software platform developed in-house by Revox offers decisive advantages. In addition to the LAN cable, it is also possible to integrate several products for a multiroom application via WLAN. Each available source and its specific content can be created individually as favorites for each user.

The concept offers every user a completely individual music experience. Personal favorites are immediately accessible for each user. Preferences of different users can be defined and operated easily and immediately.

Whether in one room or in several rooms.

Note for LAN operation: For the joint operation of several Revox Multiuser products with LAN cable, a suitable multicast-capable switch with the setting option of IGMP Snooping and Querier V2 is required.



More information about
Revox Multiuser at
<https://revox.com/en/multiuser-multiroom>

REVOX MULTIUSER APP

With the Revox Multiuser App, every available audio source in the system can be saved individually as a favorite in your own user profile. This concept creates a simple and immediately operable system, whether in one room or in several rooms.

The easiest operation in the world.
Patented by Revox.



Each user can create their own user profile in the app and make their own settings within the profile and set their personal favorites. All audio sources can be selected as favorites and also own playlists within a music source.

This user favorites function is patented by Revox.

Music content can also be added directly to the user favorites. The desired content can be added to the User Favorites via the 3-dot menu in the Play View list, which can be displayed by swiping up over the cover.

Selected user favorites can be grouped into folders via the 3-dot menu. These folders offer the option of making the User Favorites list even clearer - for example, sorted by genre or source type. User favorites folders or their contents can also be called up specifically using the wall or remote control (Revox C18 or C100).

Individual rooms can be controlled individually and zones consisting of several rooms can be set up directly in the app and operated very clearly. The WLAN connection is made via the Revox Connect function, which enables very simple and quick setup via Bluetooth.



Find out more about the
Revox Multiuser App.